

Fingerprint reader/scanner PY-F11

Parameters:

| | |
|------------------------------|---|
| Fingerprint Capacity | 1500 Templates |
| ID Card Capacity | 10,000 |
| Transaction Capacity | N/A |
| Hardware Platform | ZEM500 |
| Sensor | Optical Sensor |
| Algorithm Version | Finger V9.0 |
| Communication | RS232/485, TCP/IP |
| Access Control Interface for | 3rd party electric lock, exit button, alarm |
| Wiegand Signal | Output |
| Optional Functions | Other rf cards |
| Display | N/A |
| Power Supply | 12V DC |
| Operating Temperature | 0 °C- 45 °C |
| Operating Humidity | 20%-80% |
| Dimension | 66.4*153.5*61mm (W*H*D) |
| Net Weight | 0.46kg |
| OEM | Yes |
| SDK | Available |
| Multi languages | Available |
| bell scheduling | Built in |
| Serial and Ethernet ports | Build in |

Application: home, office, school, government, building , or other purpose.



