

## High DB 8 inch Alarm Bell

### Features and Benefits:

- \*Compatible with all the conventional fire alarm
- \*control panel
- \*High sound level up to 95dB
- \*Easy installation baracket included
- \*Steel material

Place of Origin	Guangdong, China (Mainland)
Brand Name	PROYU
Model Number	PY-JL188-8
Product Name	Alarm Bell
Dimensions	200x200x65mm
Operating Temperature Range	-10°C to 50°C
Operating Humidity Range	10% to 93% Relative Humidity, Noncondensing
System Voltage (nominal)	24 VDC (16V~ 30VDC)
Alarm Current	70 mA @ 24 VDC
Alarm Sound Intensity	Minimum 95dB





## ALARM BELL

### Install item

1. Before install please detail reading the specification.
2. Install the bell according to fire standard height.
  - Firstly open the bell cover screw, then screw the bell cover, according to the direction of the Figure 1.
  - Firstly put the plastic base to fix on the wall, pay attention the strike pin to point down, see Figure 2.
3. Switch on\*\*according to red line, the type of the black line switch on\*\*\*, which is 24V power.
4. Finally installed bell cover, and tighten up a screw to it.