

Alto DB 8 polegadas Alarme de Bell

Recursos e benefícios:

- * Compatível com todo o alarme de incêndio convencional
- * Painel de controle
- * Alto nível de som até 95dB
- * Bracket Fácil instalação incluído
- * Material de aço

Lugar de origem	Guangdong, China (continente)
Marca	PROYU
Número de modelo	PY-JL188-8
Nome do produto	Alarme de Bell
Dimensões	200x200x65mm
Faixa de temperatura operacional	-10 ° C a 50 ° C
Umidade de Operação Faixa	10% a 93% de umidade relativa, sem condensação
Tensão System (nominal)	24 VDC (16V ~ 30VDC)
Atual Alarm	70 mA @ 24 VDC
Alarme intensidade sonora	95dB mínimo





ALARM BELL

Install Item

1. Before install please detail reading the specification.
2. Install the bell according to fire standard height.
 - Firstly open the bell cover screw, then screw the bell cover, according to the direction of the figure 1.
3. Firstly put the plastic base to fix on the bell, pay attention the strike pin to enter down, see figure 2.
4. Switch on**according to red line, the type of the shock line with on***, switch on DC24 power.
5. Finally installed bell cover, and tighten up a screw to fix.