


16 zone conventional fire alarm control panel

- * Four to Sixteen Style B (Class B) Initiating Device Circuits (IDCs).
- * All zones accept two-wire smoke detectors and any normally-open contact devices.
- * Zones 1 - 16 configured as general alarm zones.
- * All circuits are power-limited and supervised, meeting the latest ULC requirements using fuseless technology.
- * Two built-in, Style Y (Class B) Notification Appliance (Signal) Circuits (NACs).
- * NACs may be programmed: Silenceable. Non-Silenceable.
- * Auto-Silence (program 5 to 20 minutes).
- * 1.25 amps of NAC power.
- * 3.0 amps of total system power.
- * Alarm, Trouble and Supervisory, Form-C relay standard.
- * 24-volt operation.
- * Resettable four-wire smoke detector power @ 500 mA.
- * Non-resettable power @ 500 mA.
- * Integral battery charger capable of charging up to 18 AH batteries (batteries over 4 AH require use of the external battery backbox, or ULC listed equivalent).
- * One-man walk-test programmable for silent or audible test.
- * Disable/Enable control per IDC.
- * Reverse polarity protection.
- * Control buttons:
 - Mode/Test/ACK (Acknowledge) Alarm Silence/Reset

CK1000
FIRE ALARM CONTROL PANEL

AC Power Fire Alarm Zone Deletion Sound1
 Battery Fault Sound Deletion Sound2
 Mute Supervisory Manual Sound3
 Silence Activate Automatic Sound4

<input type="checkbox"/>	<input type="checkbox"/>	Zone1	<input type="checkbox"/>	<input type="checkbox"/>	Zone9
<input type="checkbox"/>	<input type="checkbox"/>	Zone2	<input type="checkbox"/>	<input type="checkbox"/>	Zone10
<input type="checkbox"/>	<input type="checkbox"/>	Zone3	<input type="checkbox"/>	<input type="checkbox"/>	Zone11
<input type="checkbox"/>	<input type="checkbox"/>	Zone4	<input type="checkbox"/>	<input type="checkbox"/>	Zone12
<input type="checkbox"/>	<input type="checkbox"/>	Zone5	<input type="checkbox"/>	<input type="checkbox"/>	Zone13
<input type="checkbox"/>	<input type="checkbox"/>	Zone6	<input type="checkbox"/>	<input type="checkbox"/>	Zone14
<input type="checkbox"/>	<input type="checkbox"/>	Zone7	<input type="checkbox"/>	<input type="checkbox"/>	Zone15
<input type="checkbox"/>	<input type="checkbox"/>	Zone8	<input type="checkbox"/>	<input type="checkbox"/>	Zone16

 **CONVOY**